

TIME CHANGE INSTRUCTIONS

NEAX 1000 / 1400 / 2000 IVS / 2000 IVS-2 / 2000 IPS

With Dterm Series III, Series E and Series i Phones

CAT Mode Procedure: This is to be done while the phone is in an idle state.

1. Press <TRANSFER>
2. Press <CONF>
3. Press *
4. Press <TRANSFER>
5. Press <CONF>
6. Press #
7. "CAT MODE" displayed on LCD
8. Press <REDIAL or LNR/SPD>
9. "COMMAND" displayed on LCD
10. Press 02
11. Press <RECALL>
12. Press 2
13. Press <RECALL>
14. "02>2>Current Time" displayed on LCD
15. Input correct time using military time (HH MM SS)
16. Press <CONF>

TIME CHANGE INSTRUCTIONS

Electra Elite 48 / 192 / Electra Professional I / Electra Professional II

The Clock/Calendar can only be set from a Display Multiline Terminal that is connected to Station Port

01 or 02.

1. Press <FEATURE or FNC>
2. Press 9
3. Press #
4. Press current time (example 0,2,1,4)
5. Press <RECALL> to toggle AM/PM
6. When ONLY setting the time, press <FEATURE or FNC> to end the procedure
7. Press <HOLD> to advance to the calendar
8. Press <RECALL> to select the day of the week
9. Press # to move the cursor to the day of the month setting
10. Use the dial pad to enter the day
11. Press <RECALL> to select the month
12. Press # to move the cursor to the year setting
13. Press the last two digits of the year
14. Press <FEATURE or FNC>